

RLH Industries, Inc.

fiberopticlink.com



DS-081 2025-1001

4+1 Unmanaged 10/100 **Fixed Fiber Industrial Switch**

ETH-41-XX-1

Slim, MDI/MDI-X Auto Sensing, C1D2/NEMA TS2 (ITS) Design

RLH industrial Ethernet switches are engineered to provide reliable network performance in harsh environments. The 4+1 Fiber Switch is an unmanaged switch with 4-ports 10/100BASE-T, and 1 fiber port. The 100BASE-FX fiber port supports Single and Dual fiber configurations, Singlemode and Multimode, and ST and SC connectors.

RLH Switches are engineered with robust features and construction to meet the demands of a variety of industrial applications. The 4+1 Switch includes standard design features such as 12~48VDC dual redundant power inputs, fault alarm relay, DIN rail and wall mounting hardware, and -40°C to 75°C operating temperature range.

RLH Switches are an ideal solution for a wide range of utility and automation network environments.




4+1 Unmanaged 10/100 Fixed Fiber ST


Features

- 4 Fast Ethernet ports
- 1 Fiber 100BaseFX port, ST or SC
- Hardened to operate in -40°C to +75°C (-40°F to +167°F)
- 12-48VDC Dual redundant power inputs
- Power fault alarm relay
- Rugged IP30 housing, DIN rail & wall mountable
- UL, CE, and FCC certification
- TAA and NDAA compliant
- NEMA TS2 (ITS) compliant
- Hazardous Location UL Class 1/Div.2 certified
- 5 Year Warranty

Dimensions









Side View



















General Specifications

Data Process:	Store and Forward, CSMA/CD					
Standards:	IEEE 802.3 10Base-T (Ethernet) IEEE 802.3u 100Base-TX (Fast Ethernet) IEEE 100BaseFX Ethernet over Fiber					
Transfer Rates:	14,880pps for Ethernet port					
	148,800pps for Fast Ethernet port					
Transmission Distance:	Up to 100 Meters over twisted pair					
Transmission Speed:	Up to 100Mbps					
MAC Address:	8K table size					
Fiber Specifications:	Fiber Type	Mode	Fiber Diameter	Connector Type	Distance	
	Single Fiber Bi-Directional	Singlemode	9/125 μm	SC	20km / 12.4miles 60km / 36 miles	
	Dual Fiber	Multimode	62.5/125 50/125 μm	ST/SC	2km / 1.2 miles	
		Singlemode	9/125 μm	ST/SC	20km / 12.4 miles 60km / 36 miles 120km / 74 miles	
	Note: Distances equated using industry standard fiber and connector attenuation of 3dB/Km. Fiber condition, splices and connectors may affect actual range					
Ethernet Interface:	Auto MDI/MDI-X, Auto-Negotiation					
	(4) 10/100 Mbps					
Ethornot Doute.	(4) 10/100 Mbps					
Ethernet Ports:	(4) 10/100 Mbps (1) Fiber 100BaseFX					
		, Fault				
Ethernet Ports: LED Status Indicators:	(1) Fiber 100BaseFX					
	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2)	ctivity)	otection			
LED Status Indicators:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac	ctivity) sal, Polarity Pr		minal block)		
LED Status Indicators: Power Protection:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever	ctivity) sal, Polarity Pr		minal block)		
LED Status Indicators: Power Protection: Power Input:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant power	ctivity) sal, Polarity Pr er inputs (6 pos	sition pluggable ter	minal block)		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant power 6 Watts	ctivity) sal, Polarity Pr er inputs (6 pos	sition pluggable ter	minal block)		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant power 6 Watts 1 Relay output rated for 24	ctivity) sal, Polarity Pr er inputs (6 po: VDC @ 1 Amp 7°F)	sition pluggable ter	minal block)		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16°	ctivity) sal, Polarity Pr er inputs (6 pos VDC @ 1 Amp 7°F) 5°F)	sition pluggable ter	minal block)		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Accover Current, Power Reverond 12~48VDC redundant power 6 Watts 1 Relay output rated for 24-40°C to 75°C (-40°F to 160-40°C to 85°C (-40°F to 180-40°C)	ctivity) sal, Polarity Pr er inputs (6 pos VDC @ 1 Amp 7°F) 5°F) ing)	sition pluggable ter	minal block)		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16) -40°C to 85°C (-40°F to 18) 5% to 95% (Non-Condens)	ctivity) sal, Polarity Pr er inputs (6 pos VDC @ 1 Amp 7°F) 5°F) ing) nousing	sition pluggable ter		ctors or DIN bracket	
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity: Construction:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16 -40°C to 85°C (-40°F to 18 5% to 95% (Non-Condens) Powder coated IP30 steel in	ctivity) sal, Polarity Pr er inputs (6 pos VDC @ 1 Amp 7°F) 5°F) ing) nousing " (H), (30mm x	sition pluggable ter	Not including connec	ctors or DIN bracket	
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity: Construction: Case Dimensions:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16° -40°C to 85°C (-40°F to 18° 5% to 95% (Non-Condensi Powder coated IP30 steel for 1.18" (W) x 3.90" (D) x 5.59	ctivity) sal, Polarity Prer inputs (6 posterior) VDC @ 1 Amp 7°F) 5°F) ing) nousing " (H), (30mm x r wall mount *\	sition pluggable ter x 99mm x 142mm) ^x Wall mount bracket	Not including connects included		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity: Construction: Case Dimensions: Installation:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Action Cover Current, Power Rever 12~48VDC redundant power 6 Watts 1 Relay output rated for 24-40°C to 75°C (-40°F to 16-40°C to 85°C (-40°F to 1855% to 95% (Non-Condensite Powder coated IP30 steel F1.18" (W) x 3.90" (D) x 5.59 Standard DIN rail (TS-35) of	ctivity) sal, Polarity Prer inputs (6 posterior) VDC @ 1 Amp 7°F) 5°F) ing) nousing '" (H), (30mm x r wall mount *\ -4-2/3/4/5/6/8,	sition pluggable ter s 99mm x 142mm) ³ Wall mount bracket /11/12, CE EN6100	Not including connects included		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity: Construction: Case Dimensions: Installation: EMI:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16) -40°C to 85°C (-40°F to 18) 5% to 95% (Non-Condensi Powder coated IP30 steel F 1.18" (W) x 3.90" (D) x 5.59 Standard DIN rail (TS-35) of FCC Class A, CE EN61000	ctivity) sal, Polarity Prer inputs (6 posterior) VDC @ 1 Amp 7°F) 5°F) ing) nousing " (H), (30mm x r wall mount *\ -4-2/3/4/5/6/8, EC60068-2-27	sition pluggable ter 99mm x 142mm) * Wall mount bracket /11/12, CE EN6100 (Shock), IEC60068	Not including connects included 0-6-2, CE EN61000-6		
LED Status Indicators: Power Protection: Power Input: Max Power Consumption: Fault Output: Operating Temperature: Storage Temperature: Operating Humidity: Construction: Case Dimensions: Installation: EMI: Stability Testing:	(1) Fiber 100BaseFX Power 1 (P1), Power 2 (P2) Ethernet Ports (Link and Ac Over Current, Power Rever 12~48VDC redundant powe 6 Watts 1 Relay output rated for 24 -40°C to 75°C (-40°F to 16) -40°C to 85°C (-40°F to 18) 5% to 95% (Non-Condens) Powder coated IP30 steel for 1.18" (W) x 3.90" (D) x 5.59 Standard DIN rail (TS-35) of FCC Class A, CE EN61000 IEC60068-2-32 (Free fall), II	ctivity) sal, Polarity Prer inputs (6 posterior) VDC @ 1 Amp 7°F) 5°F) ing) nousing " (H), (30mm x r wall mount *\ -4-2/3/4/5/6/8, EC60068-2-27 0-1,UL 61010-	sition pluggable ter 99mm x 142mm) * Wall mount bracket /11/12, CE EN6100 (Shock), IEC60068 2-201, ISA 12.12.0	Not including connects included 0-6-2, CE EN61000-6		



Ordering Information

Description	Connector	Fibers	Wavelength	Distance	Part Number
Multimode	SC	Dual Fibers	1310nm	2km/1.2 miles	ETH-41-03-1
ST	ST	Dual Fibers	1310nm	2km/1.2 miles	ETH-41-04-1
Cinglomodo	SC	Single Fiber - Side A	T-1310/R-1550	20km/12.4 miles	ETH-41-10-1
Singlemode	Singlemode SC	Single Fiber - Side B	R-1310/T-1550	20km/12.4 miles	ETH-41-11-1
Cinglamada	Singlemode SC	Single Fiber - Side A	T-1310/R-1550	60km/37 miles	ETH-41-14-1
Singlemode		Single Fiber - Side B	R-1310/T-1550	60km/37 miles	ETH-41-15-1
Singlemode SC	Dual Fibers	1310nm —	20km/12.4 miles	ETH-41-40-1	
			60km/37 miles	ETH-41-41-1	
		1550nm	120km/74 miles	ETH-41-45-1	
Singlemode ST		Dual Fibers	1310nm —	20km/12.4 miles	ETH-41-50-1
	ST			60km/37 miles	ETH-41-51-1
			1550nm	120km/74 miles	ETH-41-55-1

- Single fiber (bi-directional) systems must always be paired, side A and side B
- Please contact your RLH sales representative for pricing and delivery information

Contact

By Mail:	ATTN: Sales		
	RLH Industries, Inc. 936 N. Main Street Orange, CA 92867		
By Phone:	Local	714-532-1672	
Sales/Service:	Toll Free	800-877-1672	
By Email:	info@fiberopticlink.com		
By Fax:	714-532-1885		

Support

By Email:	support@fiberopticlink.com	
By Phone:	Toll Free 855-754-2497	